

# ABB i-bus® KNX

## Outputs – Combi Switch Actuators

—  
1) = The number of ballasts is limited by the protection with B16/B20 circuit-breakers.

2) = For multiple element lamps or other types, the number of electronic ballasts must be determined using the peak inrush-current of the electronic ballasts.

3) = The maximum peak inrush-current may not be exceeded.

4) = Not intended for AC3 operation, see Technical Data for maximum AC3 current.

5) = Max. load current per device:  
8-fold = 100 A,  
16-fold = 160 A,  
24-fold = 200 A

The following table provides an overview of the rated values, switching performance, lamp loads or the number of lamps, which can be connected to a contact:

|  | SAH/S 8.6.7.1     | SAH/S 8.10.7.1     | SAH/S 8.16.7.1     |
|--|-------------------|--------------------|--------------------|
|  | SAH/S 16.6.7.1    | SAH/S 16.10.7.1    | SAH/S 16.16.7.1    |
|  | SAH/S 24.6.7.1    | SAH/S 24.10.7.1    | SAH/S 24.16.7.1    |
| <b>Range</b>   | Combi             | Combi              | Combi              |
| <b>I<sub>n</sub> rated current (A)<sup>3)</sup></b>                        | 6 A               | 10 A <sup>5)</sup> | 16 A <sup>5)</sup> |
| <b>U<sub>n</sub> rated voltage (V)</b>                                     | 230 V AC          | 230 V AC           | 230 V AC           |
| <b>AC1 operation (<math>\cos \phi = 0.8</math>) DIN EN 60947-4-1</b>       | 6 A               | 10 A               | 16 A               |
| <b>AC3 operation (<math>\cos \phi = 0.45</math>) DIN EN 60947-4-1</b>      | 6 A               | 6 A                | 6 A                |
| <b>C-Load switching capacity (200 <math>\mu</math>F)</b>                   | –                 | –                  | –                  |
| <b>Minimum switching capacity</b>  | 100 mA/12 V       | 100 mA/12 V        | 100 mA/12 V        |
| <b>DC current switching capacity (resistive load)</b>                      | 6 A/24 V =        | 6 A/24 V =         | 6 A/24 V =         |
| <b>Mechanical service life</b>   | > 10 <sup>6</sup> | > 10 <sup>6</sup>  | > 10 <sup>6</sup>  |
| <b>Electronic endurance to IEC 60947-4-1:</b>                              |                   |                    |                    |
| – Rated current AC1 (240 V/0.8)  | 100,000           | 100,000            | 100,000            |
| – Rated current AC3 (240 V/0.45)   | 6,000             | 6,000              | 6,000              |
| <b>Incandescent lamp load at 230 V AC</b>                                  | 1,200 W           | 1,200 W            | 1,200 W            |
| <b>Fluorescent lamp T5 / T8:</b>   |                   |                    |                    |
| – Uncorrected  | 800 W             | 800 W              | 800 W              |
| <b>Low-voltage halogen lamps:</b>  |                   |                    |                    |
| – Inductive transformer  | 800 W             | 800 W              | 800 W              |
| – Electronic transformer   | 1,000 W           | 1,000 W            | 1,000 W            |
| <b>Halogen lamp 230 V</b>  | 1,000 W           | 1,000 W            | 1,000 W            |
| <b>Mercury-vapour lamps:</b>   |                   |                    |                    |
| – Uncorrected  | 1,000 W           | 1,000 W            | 1,000 W            |
| – Parallel compensated   | 800 W             | 800 W              | 800 W              |
| <b>Sodium-vapour lamps:</b>  |                   |                    |                    |
| – Uncorrected  | 1,000 W           | 1,000 W            | 1,000 W            |
| – Parallel compensated   | 800 W             | 800 W              | 800 W              |
| <b>LED lamps/energy saving lamps</b>                                       | 250 W             | 250 W              | 250 W              |
| <b>Motor load</b>  | 1380 W            | 1380 W             | 1380 W             |
| <b>Max. peak inrush-current I<sub>p</sub> (150 <math>\mu</math>s)</b>      | 200 A             | 200 A              | 200 A              |
| <b>Max. peak inrush-current I<sub>p</sub> (250 <math>\mu</math>s)</b>      | 160 A             | 160 A              | 160 A              |
| <b>Max. peak inrush-current I<sub>p</sub> (600 <math>\mu</math>s)</b>      | 100 A             | 100 A              | 100 A              |
| <b>Number of electronic ballasts (T5/T8, single element):<sup>2)</sup></b> |                   |                    |                    |
| <b>18 W (ABB ballasts 1 x 18 SF)</b>                                       | 10 ballasts       | 10 ballasts        | 10 ballasts        |
| <b>24 W (ABB ballasts 1 x 24 CY)</b>                                       | 10 ballasts       | 10 ballasts        | 10 ballasts        |
| <b>36 W (ABB ballasts 1 x 36 CF)</b>                                       | 7 ballasts        | 7 ballasts         | 7 ballasts         |
| <b>58 W (ABB ballasts 1 x 58 CF)</b>                                       | 5 ballasts        | 5 ballasts         | 5 ballasts         |
| <b>80 W (Helvar EL 1 x 80 SC)</b>  | 3 ballasts        | 3 ballasts         | 3 ballasts         |

**ABB i-bus® KNX****Outputs – Combi Switch Actuators**

■ = Function is supported  
 - = Function is not supported

The following table provides an overview of the functions possible with the Switch Actuators and their application programs:

|  | SAH/S 8.6.7.1       | SAH/S 8.10.7.1      | SAH/S 8.16.7.1      |
|--|---------------------|---------------------|---------------------|
|  | SAH/S 16.6.7.1      | SAH/S 16.10.7.1     | SAH/S 16.16.7.1     |
|  | SAH/S 24.6.7.1      | SAH/S 24.10.7.1     | SAH/S 24.16.7.1     |
| <b>Range</b>                                       | Combi               | Combi               | Combi               |
| Type of installation                               | DIN-Rail            | DIN-Rail            | DIN-Rail            |
| Number of outputs (Switch [Blind])                 | 8 [4]/16[8]/24 [12] | 8 [4]/16[8]/24 [12] | 8 [4]/16[8]/24 [12] |
| Module width (space unit)                          | 4/8/12              | 4/8/12              | 4/8/12              |
| Manual operation                                   | ■                   | ■                   | ■                   |
| Contact position display                           | ■                   | ■                   | ■                   |
| I <sub>n</sub> rated current (A)                   | 6 A                 | 10 A                | 16 A                |
| Current detection                                  | -                   | -                   | -                   |
| <b>Switch function</b>                             |                     |                     |                     |
| - ON/OFF delay                                     | ■                   | ■                   | ■                   |
| - Central ON/OFF                                   | ■                   | ■                   | ■                   |
| - Staircase light                                  | ■                   | ■                   | ■                   |
| - Warning before end of staircase lighting         | ■                   | ■                   | ■                   |
| - Staircase lighting time set via object           | ■                   | ■                   | ■                   |
| - Flashing   | ■                   | ■                   | ■                   |
| - Switch response can be set (N.O./N.C.)           | ■                   | ■                   | ■                   |
| - Thresholds                                       | ■                   | ■                   | ■                   |
| <b>Current detection</b>                           | -                   | -                   | -                   |
| - Threshold value monitoring                       | -                   | -                   | -                   |
| - Measured value detection                         | -                   | -                   | -                   |
| <b>Function Scene</b>                              | ■                   | ■                   | ■                   |
| <b>Function Logic (independent of output)</b>      |                     |                     |                     |
| - Logic AND function                               | ■                   | ■                   | ■                   |
| - Logic OR function                                | ■                   | ■                   | ■                   |
| - Logic XOR function                               | ■                   | ■                   | ■                   |
| - Gate function                                    | ■                   | ■                   | ■                   |
| <b>Priority object/forced operation</b>            | ■                   | ■                   | ■                   |
| <b>Blind/Roller Shutter function</b>               |                     |                     |                     |
| - Blind/Shutter control                            | ■                   | ■                   | ■                   |
| - Wind/Rain/Frost alarm                            | ■                   | ■                   | ■                   |
| - Central up/down/position/stop                    | ■                   | ■                   | ■                   |
| - Automatic mode (sun)                             | ■                   | ■                   | ■                   |
| - Pause on change in direction                     | ■                   | ■                   | ■                   |
| - Referent movement                                | ■                   | ■                   | ■                   |
| - Travel limitation                                | ■                   | ■                   | ■                   |
| - Adjustable delay time for drives                 | ■                   | ■                   | ■                   |
| <b>Special functions</b>                           |                     |                     |                     |
| - Request status values                            | ■                   | ■                   | ■                   |
| - Template pages                                   | ■                   | ■                   | ■                   |
| - Default position on bus voltage failure/recovery | ■                   | ■                   | ■                   |
| - Status messages                                  | ■                   | ■                   | ■                   |